
Led Net - Suspension - App Compatible

Michele De Lucchi Alberto Nason



DESCRIPTION





LUMINAIRE

- Watt: 43W

- Voltage: **220-240V**

- Delivered lumens output: 2502lm

- CCT: **3000K** - Efficiency: **81%**

- Efficacy: 58.19lm/W

- CRI: 80

Notes

LEDs included

PRODUCT CODE: 1575050APP

FEATURES

Article Code: 1575050APPColour: Polished whiteInstallation: Suspension

- Material: Aluminium, methacrylate

Series: Design CollectionEnvironment: IndoorArea contract: Hospitality

- Emission: **Direct**

- design by: Michele De Lucchi, Alberto Nason

DIMENSIONS

Height: cm 2.4Diameter: cm 65

- Max Height from ceiling: cm 200

- Glow Wire Test: 650°

SOURCES INCLUDED

Category: LedNumber: 17Watt: 2.17W

Delivered lumens output: 153lmColor temperature (K): 3000K

- CRI: **80**

- Color Tolerance: MacAdam 3SDCM

- Efficacy: 71lm/W

- Service Life: **50000-L70**



Accessories



Device for switching and controlling Artemide App products. Max N.3 inputs for external push buttons. Mains power supply required. To be installed inside flush mounting boxes or junction boxes. DV1080APP




Led Net - Ceiling - App Compatible

Michele De Lucchi Alberto Nason



DESCRIPTION





LUMINAIRE

- Watt: 43W

- Voltage: 220-240V

- Delivered lumens output: 2502lm

- CCT: **3000K**- Efficiency: **81%**

- Efficacy: 58.19lm/W

- CRI: 80

Notes

LEDs included

PRODUCT CODE: 1594050APP

FEATURES

Article Code: 1594050APPColour: Polished whiteInstallation: Ceiling

- Material: Aluminium, methacrylate

Series: Design CollectionEnvironment: IndoorArea contract: Hospitality

- Emission: **Direct**

- design by: Michele De Lucchi, Alberto Nason

DIMENSIONS

Height: cm 7Diameter: cm 65Glow Wire Test: 650°

SOURCES INCLUDED

Category: LedNumber: 17Watt: 2.17W

Delivered lumens output: 153lmColor temperature (K): 3000K

- CRI: 80

- Color Tolerance: MacAdam 3SDCM

- Efficacy: **71lm/W**

- Service Life: 50000-L70



Accessories



Device for switching and controlling Artemide App products. Max N.3 inputs for external push buttons. Mains power supply required. To be installed inside flush mounting boxes or junction boxes. DV1080APP

